

## **BOLLARD LIGHT**

E 259/E 260



Please read instructions before commencing installation and retain for future reference.


## **SPECIFICATIONS:**

- Fitting: ALUMINUM +PC Lamp type: LED 12W 3000K
- Protection against electric shock: CLASS I,. Requires earth connection.
- Ingress Protection: IP65. Protection against entry of dust. Protected against water jets.
- Quality/Corrosive rating: QC21: Burning period: 12hrs/24hr cycle. Commercial use, indoor mainly - painted or plated metals. Not for use in corrosive environments.
- Driver: Included.



## **Connecting the Terminal Block**

Connect main supply (brown - live, blue - neutral, green/yellow - earth) into terminal block making sure all connections are tight.



## **INSTALLATION INSTRUCTIONS:**

Electrical products can cause death, injury, or damage to property. Installation of this product must be carried out by a qualified electrician.

- Ensure mains supply is switched off.
- Insert masonry plugs into mounting surface.
- Fit mounting bracket onto mounting surface with self-tapping screws.
- Connect wires according to color (White to White, Black to Black). Connect all earth lug together onto the crossbar with green screw to tight.
- Fit ceiling plate onto mounting bracket with nuts.
- Reconnect power.











